


# NASA TECH BRIEF



NASA Tech Briefs announce new technology derived from the U.S. space program. They are issued to encourage commercial application. Tech Briefs are available on a subscription basis from the National Technical Information Service, Springfield, Virginia 22151. Requests for individual copies or questions relating to the Tech Brief program may be directed to the Technology Utilization Division, NASA, Code UT, Washington, D.C. 20546.

## AC-Coupled Ultrahigh Input Impedance Amplifier

High input impedance and low input capacitance have been achieved with a conventional unity gain buffer amplifier modified by the addition of positive feedback. The circuit, which is stable over a temperature range of 25° to 70°C, achieves input impedances of several hundred megohms and input capacitances of less than 1 picofarad (pf).



$$C_F = 68 \text{ Picofarads} \quad C_{IN} \approx 2 \text{ Picofarads}$$

$$C_A = 0.1 \text{ Microfarad}$$

$$R_A = 500\Omega \quad R_B = 10K$$

The high input impedance is obtained by positive feedback through capacitor  $C_A$  to the plus (+) input of the amplifier (see fig.). The input capacitance plus the capacitance to ground is  $C_{IN}$ , which can be cancelled by adding the feedback capacitor  $C_F$  and ad-

justing resistor  $R_A$ . The following relationship applies:

$$\frac{R_A}{R_B} \approx \frac{C_{IN}}{C_F}$$

Low frequency response is determined primarily by capacitor  $C_A$ , for which an electrolytic capacitor can be used. High frequency response is limited by the operational amplifier. The value of  $R_A$  is determined by applying a square wave to the input and adjusting  $R_A$  to produce an acceptable square wave output, in much the same manner that a 10X scope probe is adjusted.

The circuit was used to amplify a 5  $\mu$ sec wide pulse coupled through a capacitor of less than 1 pf. Slew rate for the circuit was approximately 0.5 V/ $\mu$ sec.

Gains other than unity can be obtained, but this would probably be simpler if another separate amplifier is used.

### Note:

No additional documentation is available. Specific questions, however, may be directed to:

Technology Utilization Officer  
 Lewis Research Center  
 21000 Brookpark Road  
 Cleveland, Ohio 44135  
 Reference: B70-10651

### Patent status:

No patent action is contemplated by NASA.

Source: Arthur G. Birchenough  
 Lewis Research Center  
 (LEW-11154)

Category 01